Install the Drivers & Software

If your PIXMA mg7120 has already been set up on your wireless network, it is only necessary to install the software and drivers to the computer(s) on your wireless network. It is not necessary to reset the printer or make additional settings.

To begin setup of your PIXMA mg7120 to additional computers on on your wireless network, insert the Setup CD-ROM* in your computer.



The setup program will start automatically.

*If you don't have or cannot use the Setup CD-ROM, follow the steps below to start the setup.

- <u>Download the software</u> (click the link to download)
- Double-click the downloaded .exe file (Win-mg7100-1_1-ucd.exe)

If the User Account Control dialog box appears during the setup, click Yes or Continue.

Install the Drivers & Software

Click Next on the initial screen

Canon PIXMA MG7100 series



PIXMA MG7100 series

You can select whether to use this printer via USB connection or LAN connection. Follow the on-screen instructions to select the connection method.

Network setup is required when using the printer via LAN connection. If the setup is already completed, the connection is confirmed automatically. If the setup is not completed, follow the on-screen instructions to set up the printer.



Exit



Install the Drivers & Software

Continue following on-screen instructions. On the **Software Installation List**, select *software to install and click **Next**.

***MP Drivers** is required and cannot be deselected. We recommend installing **My Image Garden** and **Quick Menu** to take full advantage of the printer's features.

'he selected software will be installed. Make s lick [Next]	sure that the software you want to	install is selected, and the
liot [rioti].		
✓ MP Drivers	260 MB	Drive C: 186056 MB fre
🗹 User's Manual	10 MB	space Total used space: 1064 MB
✓ My Printer	14 MB	
☑ My Image Garden	680 MB	
🗹 Quick Menu	40 MB	
✓ Easy-WebPrint EX	60 MB	
XPS Driver	130 MB	
		Select All

Complete the Setup

Continue following on-screen instructions.

When the **Setup Completion** dialog box appears, click **Complete**.

Setup Completion			
A DIDIONAL	Setup has been completed. To check the setup results, click View Setup Results.		
Carrier Contraction	Model: SSID:	Canon MG7100 series MyNetworkName	
		View Setup Results	
Help		Complete	

At this point, setup of the printer and network is complete. Continue to follow any remaining on-screen instructions to finish and exit the setup program.