

Menu Route Map

Network Settings

- Select Wired/Wireless LAN
 - Wired LAN, Wireless LAN
- Wireless LAN Settings
 - WPS Push Button Mode
 - WPS PIN Code Mode
 - SSID Settings
 - Select Access Point
 - Enter Manually
 - Security Settings
 - None
 - WEP (802.11 Authentication)
 - Open System, Shared key
 - WPA/WPA2-PSK (WPA/WPA2 Encryption Method)
 - Auto, AES-CCMP
 - Power Save Mode
 - Off, On
 - Wireless LAN Information
 - MAC Address
 - Wireless LAN Status
 - Latest Error Information
 - Channel
 - SSID Settings
 - Security Settings
 - Power Save Mode
- TCP/IP Settings
 - IPv4 Settings
 - IP Address Settings
 - Auto Acquire
 - Select Protocol
 - Off, DHCP, BOOTP, RARP
 - Auto IP
 - Off, On
 - Manually Acquire
 - IP Address: 0.0.0.0
 - Subnet Mask: 0.0.0.0
 - Gateway Address: 0.0.0.0
 - Check Settings
 - Auto Acquire
 - IP Address
 - Subnet Mask
 - Gateway Address
 - PING Command
 - DNS Settings
 - DNS Server Settings
 - Primary DNS Server: 0.0.0.0
 - Secondary DNS Server: 0.0.0.0
 - DNS Host Name/Domain Name Settings
 - Host Name
 - Domain Name
 - DNS Dynamic Update Settings
 - Off, On (DNS Dynamic Update Interval)
 - 0 to 24 to 48 (hr.)
 - mDNS Settings
 - Off, On (mDNS Name)
 - DHCP Option Settings
 - Acquire Host Name
 - Off, On
 - DNS Dynamic Update
 - Off, On
 - IPv6 Settings
 - Use IPv6
 - Off, On, Check Settings
 - Stateless Address Settings
 - Off, On, Check Settings
 - Use DHCPv6
 - Off, On, Check Settings
 - Stateful Address
 - Prefix Length
 - DNS Settings
 - DNS Host Name/Domain Name Settings (Use IPv4 Host/Domain)
 - Off, On
 - Host Name
 - Domain Name
 - DNS Dynamic Update Settings
 - Off, On
 - Register Manual Address
 - Off, On
 - Register Stateful Address
 - Off, On
 - Register Stateless Address
 - Off, On
 - DNS Dynamic Update Interval
 - 0 to 24 to 48 (hr.)
 - mDNS Settings
 - Off, On (Use IPv4 Name for mDNS)
 - Off (mDNS Name), On
 - LPD Print Settings
 - Off, On
 - RAW Print Settings
 - Off, On
 - WSD Settings
 - WSD Print Settings
 - Use WSD Print
 - Off, On
 - Use WSD Browsing
 - Off, On
 - WSD Scan Settings
 - Use WSD Scan
 - Off, On
 - Use Computer Scan
 - Off, On
 - Use Multicast Discovery
 - Off, On
 - Use HTTP
 - Off, On
 - Port Number Settings
 - LPD
 - 1 to 515 to 65535
 - RAW
 - 1 to 9100 to 65535
 - WSD Multicast Discovery
 - 1 to 3702 to 65535
 - HTTP
 - 1 to 80 to 65535
 - SNMP
 - 1 to 161 to 65535
 - MTU Size
 - 1300, 1400, 1500
 - SNMP Settings
 - SNMPv1 Settings
 - Off, On
 - Community Name 1 Settings
 - Off, On
 - Community Name 2 Settings
 - Off, On
 - Dedicated Community Settings
 - Off, On
 - Acquire Printer Management Information from Host
 - Off, On
 - Dedicated Port Settings
 - Off, On
 - Waiting Time for Connection at Startup
 - 0 to 300 (sec.)
 - Ethernet Driver Settings
 - Auto Detect
 - Off, On
 - Communication Mode
 - Half Duplex, Full Duplex
 - Ethernet Type
 - 10BASE-T, 100BASE-TX
 - Mac Address
 - Initialize Network Settings

Output Report

- User Data List

Preferences

- Display Settings
 - Language*¹
 - English, French, Spanish, Portuguese
 - Remote UI Language*¹
 - English, French, Spanish, Portuguese
 - Contrast
 - 5 Levels
 - Invert Screen Colors
 - Off, On
 - Millimeter/Inch Entry Switch*¹
 - Millimeter, Inch
 - Gram/Pound Switch*²
 - Gram, Pound
 - Message Display Time
 - 1 to 2 to 5 (sec.)
 - Scrolling Speed
 - Slow, Standard, Fast
 - Cursor Movement
 - Auto, Manual

Settings marked with an asterisk (*1) have different defaults depending on the country or region of purchase.
Settings marked with an asterisk (*2) are unavailable depending on the country or region of purchase.

Adjustment/Maintenance

- Toner Save
 - Copy
 - Off, On
- Special Processing
 - Special Mode U
 - Off, On
 - Special Mode V
 - Off, Mode 1, Mode 2, Mode 3
 - Special Mode Z
 - Off, Mode 1, Mode 2, Mode 3, Mode 4
 - Special Mode B
 - Off, Mode 1, Mode 2, Mode 3
 - Special Mode C
 - Off, On
 - Special Mode D
 - Copy
 - Off, On
 - Print
 - Off, On
 - Special Mode I
 - Off, On
 - Special Mode J
 - Off, On
 - Special Mode K
 - Off, On
- Clean Fixing Assembly

Timer Settings

- Quiet Mode Time
 - Start Time
 - Off, On
 - Start time setting to enter quiet mode
 - End Time
 - Off, On
 - Stop time setting to exit quiet mode
- Date/Time Settings
 - Date Format*
 - YYYY MM/DD, MM/DD/YYYY, DD/MM/YYYY
 - Time Format
 - 12 Hour (AM/PM), 24 Hour
 - Current Date/Time Settings
 - Daylight Saving Time Settings*
 - Off, On
 - Start: Month, Week, Day
 - End: Month, Week, Day
- Auto Sleep Time
 - 5 to 30 (min.)
- Auto Reset Time
 - 0=Off (Auto Reset is disabled.), 1 to 2 to 9 (min.)
- Function After Auto Reset
 - Default Function, Selected Function
- Auto Offline Time
 - 0=Off (The machine remains online.), 1 to 5 to 60 (min.)

Settings marked with an asterisk (*) have different defaults depending on the country or region of purchase.

Copy Settings

- Change Default Settings
 - Number of Copies
 - 1 to 99
 - Density
 - 4 to 0 to +4, Auto Density
 - Original Type
 - Text, Text/Photo (High Speed), Text/Photo, Photo
 - Copy Ratio
 - Custom Ratio, 100% (Direct), 400% (Max), 200%, 129% STMT-LTR, 78% LGL-LTR, 64% LTR-STMT, 50%, 25%(Min)
 - N on 1
 - Off, 2 on 1, 4 on 1, ID Card Copy, Select Layout
 - Collate
 - Off, On
 - Sharpness
 - 7 Levels
- Correct Density
 - 4 to 0 to +4

Scan Settings

- Shortcut Key Settings
 - Register
 - Scan -> PC1
 - Off
 - USB Connection
 - Color Scan, B&W Scan, Custom 1, Custom 2
 - Network Connection
 - Color Scan, B&W Scan, Custom 1, Custom 2
 - Scan -> PC2
 - Off
 - USB Connection
 - Color Scan, B&W Scan, Custom 1, Custom 2
 - Network Connection
 - Color Scan, B&W Scan, Custom 1, Custom 2
 - Confirm Destination
 - Scan -> PC1
 - Scan -> PC2

Printer Settings

- Action When Paper Size Mismatch
 - Force Output, Display Error
- Mobile Print Halftones
 - Gradation, Error Diffusion
- AirPrint Speed/Image Quality Priority
 - Speed Priority, Image Quality Priority

System Management Settings

- Network Settings
 - Network Settings
- System Manager Information Settings
 - System Manager PIN
 - System Manager Name
- Device Information Settings
 - Device Name
 - Location
- Security Settings
 - IPv4 Address Filter
 - Off, On
 - IPv6 Address Filter
 - Off, On
 - MAC Address Filter
 - Off, On
- Select Country/Region
 - United States (US), Canada (CA), Brazil (BR), Mexico (MX), Other
- Remote UI Settings
 - Use Remote UI
 - Off, On
- Auto Online for Remote Scan
 - Off, On
- Use as USB Device
 - Off, On
- Enable Product Extended Survey Program
 - Off, On
- Displ. Consumbls. Info (RUI/Toner Status)
 - Displ. Consumables Purchase Button (RUI)
 - Off, On
 - Toner Status Settings
 - Off, On (Displ. Purchase Button)
 - Off, On
- PDL Selection (Plug and Play)
 - Network
 - UFRII LT, UFRII LT (XPS)
 - USB
 - UFRII LT, UFRII LT (XPS)
- Update Firmware
 - Via PC, Via Internet, Version Information
- Initialize System Management Settings
 - Network Settings
 - System Manager Information Settings
 - Device Information Settings
 - Security Settings
 - Remote UI Settings
 - Auto Online for Remote Scan
 - Use as USB Device
 - Enable Product Extended Survey Program
 - Displ. Consumbls. Info (RUI/Toner Status)
 - PDL Selection (Plug and Play)
 - Initialize All
- Initialize All Data/Settings

Initialize Menu

- Preferences
- Timer Settings
- Copy Settings
- Scan Settings
- Printer Settings
- Adjustment/Maintenance
- Initialize All