

# Menu Route Map

**Network Settings**

- Select Wired/Wireless LAN
  - Wired LAN, Wireless LAN
- Wireless LAN Settings
  - WPS Push Button Mode
  - WPS PIN Code Mode
  - SSID Settings
    - Select Access Point, Manual Settings
  - Wireless LAN Information
    - MAC Address
    - Wireless LAN Status
    - Latest Error Information
    - Channel
    - SSID Settings
    - Security Settings
- TCP/IP Settings
  - IPv4 Settings
    - IP Address Settings
      - Auto Obtain
        - Select Protocol: Off, **DHCP**, BOOTP, RARP
        - Auto IP: Off, **On**
      - Manual Obtain
        - IP Address: 0.0.0.0
        - Subnet Mask: 0.0.0
        - Gateway Address: 0.0.0.0
      - View Setting:
        - Auto Obtain
        - IP Address
        - Subnet Mask
        - Gateway Address
    - PING Command
    - DNS Settings
      - DNS Server Settings
        - Primary DNS Server: 0.0.0.0
        - Secondary DNS Server: 0.0.0.0
      - DNS Host Name/Domain Name Settings
        - Host Name
        - Domain Name
      - DNS Dynamic Update Settings: **Off**, **On**
    - mDNS Settings
      - Off
      - On**
        - mDNS Name
  - IPv6 Settings
    - Use IPv6
      - Off**, **On**, View Settings
    - Stateless Address Settings
      - Off, **On**, View Settings
    - Use DHCPv6
      - Off, **On**, View Settings
    - DNS Settings
      - DNS Host Name/Domain Name Settings
        - Use IPv4 Host/Domain
        - Off (Host Name, Domain Name), **On**
      - DNS Dynamic Update Settings
        - Off
        - On**
          - Register Manual Address: **Off**, **On**
          - Register Stateful Address: **Off**, **On**
          - Register Stateless Address: **Off**, **On**
    - mDNS Settings
      - Off
      - On**
        - Use IPv4 Name for mDNS: **Off**, **On**
  - LPD Settings
    - Off, **On**
  - RAW Settings
    - Off, **On**
  - WSD Settings
    - WSD Print Settings
      - Use WSD Print: **Off**, **On**
      - Use WSD Browsing: **Off**, **On**
    - WSD Scan Settings
      - Use WSD Scan: **Off**, **On**
      - Use Computer Scan: **Off**, **On**
      - Use Multicast Discovery: **Off**, **On**
  - Use HTTP
    - Off, **On**
  - Port Number Settings
    - LPD: 0 to **515** to 65535
    - RAW: 0 to **9100** to 65535
    - HTTP: 0 to **80** to 65535
    - SNMP: 0 to **161** to 65535
  - IP Address Range Settings
    - IPv4 Address Range Settings
      - Off
        - Only Allowed Addresses On
        - Only Denied Addresses On
      - Allowed/Denied Addresses On
    - IPv6 Address Range Settings
      - Off
        - Only Allowed Addresses On
        - Only Denied Addresses On
      - Allowed/Denied Addresses On
  - Allowed RX MAC Address Settings
    - Off, **On**
- SNMPv1 Settings
  - SNMPv1 Settings
    - Off
    - On**
      - Community Name 1: **public**
      - Community Name 2: **public**
      - MIB Access Permission 1: Read/Write, **Read Only**
      - MIB Access Permission 2: Read/Write, **Read Only**
      - Dedicated Community Settings
        - Off, **Read/Write**, Read Only
      - Printer Management Information From Host:
        - Off, **On**
- Dedicated Port Settings
  - Off, **On**
- Startup Settings
  - 0 to 300 (sec.)
- Ethernet Driver Settings
  - Auto Detect
    - Off
      - Communication Mode: **Half Duplex**, Full Duplex
      - Ethernet Type: **10Base-T**, 100Base-TX
    - On**
  - Mac Address

**Preferences**

- Sound Volume Control
  - Fax Tone
    - Off
    - On**
      - Fax Volume: **1** to 5
  - Ring Tone
    - Off
    - On**
      - Ring Tone Volume: **1** to 5
  - TX Done Tone
    - Off
    - On**
      - TX Done Volume: **1** to 5
      - Only When Error Occurs
        - TX Done Volume: **1** to 5
  - RX Done Tone
    - Off
    - On**
      - RX Done Volume: **1** to 5
      - Only When Error Occurs
        - RX Done Volume: **1** to 5
  - Scanning Done Tone
    - Off
    - On**
      - Scanning Done Volume: **1** to 5
      - Only When Error Occurs
        - Scanning Done Volume: **1** to 5
  - Entry Tone
    - Off
    - On**
      - Entry Tone Volume: **1** to 5
  - Invalid Entry Tone
    - Off
    - On**
      - Invalid Entry Tone Vol: **1** to 5
  - Warning Tone
    - Off
    - On**
      - Warning Tone Volume: **1** to 5
  - Job Done Tone
    - Off
    - On**
      - Job Done Tone Volume: **1** to 5
  - Energy Saver Alert
    - Off
    - On**
      - Energy Saver Alert Vol: **1** to 5
  - Original in Feeder Detection Tone
    - Off
    - On**
      - Orig. Detection Tone: **1** to 5
- Display Settings
  - Select Default Screen
    - Copy, Fax, Scan
  - Language
    - English**, French, Portuguese, Spanish
  - Remote UI Language
    - English**, French, Portuguese, Spanish
  - Contrast
    - 2 to **0** to +2
  - Invert Screen Colors
    - Off, **On**
  - mm/Inch Entry Switch
    - mm, **Inch**
  - Gram/Pound Switch
    - Gram, **Pound**
  - Message Display Time
    - 1 to **2** to 5 (sec.)
  - Scrolling Speed
    - Slow, **Normal**, Fast
  - Cursor Movement
    - Auto**, Manual
- Toner Saver Mode
  - Copy
    - Off, **On**
  - Fax
    - Off, **On**

**Timer Settings**

- Quiet Mode Time Settings
  - Start Time
    - Off, **On** - AM, PM
  - End Time
    - Off, **On** - AM, PM
- Time & Date Settings
  - Date Display Type
    - YYYY MM/DD, **MM/DD/YYYY**, DD/MM YYYY
  - 12/24 Hour Clock
    - 12 Hour (AM/PM)**, 24 Hour
  - Current Time Settings
    - Daylight Savings
      - Off
      - On**
        - Start (M/W/D), End (M/W/D)
  - Auto Sleep Time
    - 5 to 240 (min.)
  - Auto Reset Time
    - 0=Off, 1 to **2** to 9 (min.)
  - Screen After Auto Reset
    - Default Screen**, Selected Screer
  - Auto Offline Time
    - 0=Off, 1 to **5** to 60 (min.)

**Copy Settings**

- Change Defaults
- Correct Density
  - 4 to **0** to +4

**Fax TX Settings**

- Basic Settings
  - Register Unit Telephone Number
  - Register Unit Name
  - Select Line Type
    - Pulse, **Tone**
  - Public Line Connection
    - Direct**, Adapter 1, Adapter 2
  - Off-Hook Alarm
    - Off
    - On**
      - Off-Hook Alarm Volume: **1** to 5
- TX Function Settings
  - Change Defaults
  - ECM TX
    - Off, **On**
  - Pause Time
    - 1 to **2** to 15 (sec.)
  - Auto Redial
    - Off
    - On**
      - Redial Times: 1 to **2** to 10 (times)
      - Redial Interval : **2** to 99 (min.)
      - Redial When Err Occurs: **Off**, **On**
  - Sender ID
    - Off
    - On**
      - Print Location: On Image, **Above Image**
      - Mark No. as: TEL/FAX, **FAX**, TEL
  - Check Dial Tone Before Sending
    - Off, **On**

**Fax RX Settings**

- RX Function Settings
  - ECM RX
    - Off, **On**
  - Incoming Ring
    - Off
    - On**
      - Ring Times: 1 to **2** to 99 (times)
  - Remote RX
    - Off
    - On**
      - Remote RX ID: 00 to **25** to 99
  - Switch to Auto RX
    - Off
    - On**
      - Ring Time till Auto RX: 1 to 15 to 99 (seconds)
- RX Print Settings
  - 2-Sided Printing
    - Off, **On**
  - Reduce RX Size
    - Off
    - On**
      - Reduction Ratio: **Auto**, 97, 95, 90, 75 (%)
      - Reduction Direction: Vertical/Horizontal, **Vertical Only**
  - RX Page Footer
    - Off, **On**
  - Continue Print. When Toner Is Nearly Out
    - Off, **On**

**Scan Settings**

- Shortcut Key Settings
  - Register
    - Scan > PC1
      - Off
      - On**
        - USB Connection
          - Color Scan**, B&W Scan, Custom 1, Custom 2
        - Network Connection
          - Color Scan**, B&W Scan, Custom 1, Custom 2
    - Scan > PC2
      - Off
      - On**
        - USB Connection
          - Color Scan**, B&W Scan, Custom 1, Custom 2
        - Network Connection
          - Color Scan**, B&W Scan, Custom 1, Custom 2
  - Confirm Destination

**Adjustment/Maintenance**

- Special Processing
  - Special Mode U
    - Off, **On**
  - Special Mode V
    - Off, **On**, Mode 1, Mode 2, Mode 3
  - Special Mode Z
    - Copy: Off, Mode 1, **Mode 2**, Mode 3, Mode 4
    - Fax: Off, Mode 1, **Mode 2**, Mode 3, Mode 4
  - Special Mode B
    - Off, **On**, Mode 1, Mode 2, Mode 3
  - Special Mode C
    - Off, **On**
  - Special Mode D
    - Copy: **Off**, **On**
    - Print: **Off**, **On**
  - Special Mode I
    - Off, **On**
  - Special Mode J
    - Off, **On**
  - Special Mode K
    - Off, **On**
- Clean Fixing Unit

**System Settings**

- Network Settings
- System Manager Information Settings
  - System Manager PIN
    - Up to 7 digits
  - System Manager Name
    - Up to 32 characters
- Device Information Settings
  - Device Name
    - Up to 32 characters
  - Location
    - Up to 32 characters
- Communication Management Settings
  - Fax Settings
    - TX Start Speed: **33600** bps, 14400 bps, 9600 bps, 7200 bps, 4800 bps, 2400 bps
    - RX Start Speed: **33600** bps, 14400 bps, 9600 bps, 7200 bps, 4800 bps, 2400 bps
  - Memory Lock Settings
    - Off
    - On**
      - Memory Lock PIN
      - Report Print: **Off**, **On**
      - Memory Lock Time
        - Off
        - On**
          - Memory Lock Start Time
          - Memory Lock End Time
- Select Country/Region
  - United States (US)**, Canada (CA), Brazil (BR), Mexico (MX), Other
- Remote UI On/Off
  - Off, **On**
- Restrict TX Function
  - Address Book PIN
  - Restrict New Destinations
    - Off, **On**
  - Allow Fax Driver TX
    - Off, **On**
  - Restrict Sending From History
    - Off, **On**
  - Fax No. Confirmation Re-Entry
    - Off, **On**
  - One-Touch/Coded Dial TX Confirmation
    - Off, **On**
  - Restrict Sequential Broadcast
    - Off, Confirm Sequential Broadcast, Reject Sequential Broadcast
- Display Job History
  - Off, **On**
- USB Device On/Off
  - Off, **On**
- Import/Export Address Book
- Select PDL (Plug-n-Play)
  - Network
    - FAX, **UFRII LT**, UFRII LT(XPS)
  - USB
    - UFRII LT**, UFRII LT(XPS)
- Update Firmware
- Initialize Address Book
- Initialize System Settings
  - Network Settings
  - System Manager Information Settings
  - Device Information Settings
  - Communication Management Settings
  - Remote UI On/Off
  - Restrict TX Function
  - Display Job History
  - USB Device On/Off
  - Select PDL (Plug-n-Play)
  - Initialize All

**Initialize Menu**

- Preferences
- Timer Settings
- Copy Settings
- Scan Settings
- Fax TX Settings
- Fax RX Settings
- Special Processing
- Initialize All