

Menu Route Map

Network Settings

- Select Wired/Wireless LAN
 - Wired LAN, Wireless LAN
- Wireless LAN Settings
 - WPS Push Button Mode
 - WPS PIN Code Mode
 - SSID Settings
 - Select Access Point
 - Manual Settings
 - Wireless LAN Information
 - MAC Address
 - Wireless LAN Status
 - Latest Error Information
 - Channel
 - SSID Settings
 - Security Settings
- TCP/IP Settings
 - IPv4 Settings
 - IP Address Settings
 - Auto Obtain
 - Select Protocol: Off, **DHCP**, BOOTP, RARP
 - Auto IP: Off, **On**
 - Manual Obtain
 - IP Address: 0.0.0.0
 - Subnet Mask: 0.0.0.0
 - Gateway Address: 0.0.0.0
 - View Settings
 - Auto Obtain
 - IP Address
 - Subnet Mask
 - Gateway Address
 - PING Command
 - DNS Settings
 - DNS Server Settings
 - Primary DNS Server: 0.0.0.0
 - Secondary DNS Server: 0.0.0.0
 - DNS Host Name/Domain Name Settings
 - Host Name
 - Domain Name
 - DNS Dynamic Update Settings
 - Off
 - On
 - DNS Dynamic Updt. Time: 0 to **24** to 48 (hr.)
 - mDNS Settings
 - Off
 - On: mDNS Name
 - DHCP Option Settings
 - Acquire Host Name: Off, **On**
 - DNS Dynamic Update: Off, **On**
 - IPv6 Settings
 - Use IPv6
 - Off
 - On
 - View Settings
 - Link-Local Address
 - Prefix Length
 - Stateless Address Settings
 - Off, **On**, View Settings
 - Use DHCPv6
 - Off, **On**, View Settings
 - DNS Settings
 - DNS Host Name/Domain Name Settings (Use IPv4 Host/Domain)
 - Off (Host Name, Domain Name), **On**
 - DNS Dynamic Update Settings
 - Off
 - On
 - Register Manual Address: Off, **On**
 - Register Stateful Address: Off, **On**
 - Register Stateless Address: Off, **On**
 - DNS Dynamic Update Time: 0 to **24** to 48 (hr.)
 - mDNS Settings
 - Off
 - On
 - Use IPv4 Name for mDNS
 - Off (mDNS Name), **On**
 - WINS Settings
 - WINS Resolution
 - Off
 - On (WINS Server Address: 0.0.0.0)
 - Scope ID
 - LPD Settings
 - Off, **On**
 - RAW Settings
 - Off, **On**
 - WSD Settings
 - WSD Print Settings
 - Use WSD Print: Off, **On**
 - Use WSD Browsing: Off, **On**
 - WSD Scan Settings
 - Use WSD Scan: Off, **On**
 - Use Computer Scan: Off, **On**
 - Use Multicast Discovery: Off, **On**
 - Use HTTP
 - Off, **On**
 - Port Number Settings
 - LPD: 1 to **515** to 65535
 - RAW: 1 to **9100** to 65535
 - HTTP: 1 to **80** to 65535
 - POP3 RX: 1 to **110** to 65535
 - SMTP TX: 1 to **25** to 65535
 - SNMP: 1 to **161** to 65535
 - WSD Search: 1 to **3702** to 65535
 - Multicast Discovery: 1 to **427** to 65535
 - MTU Size
 - 1300, 1400, **1500**
- SNMP Settings
 - SNMPv1 Settings
 - Off
 - On
 - Community Name 1: **public**
 - Community Name 2: Not Set
 - MIB Access Permission 1: **Read Only**, Read/Write
 - MIB Access Permission 2: **Read Only**, Read/Write
 - Dedicated Community Settings: Off, Read/Write, **Read Only**
 - SNMPv3 Settings
 - Off, **On**
 - Printer Management Information From Host
 - Off, **On**
- Dedicated Port Settings
 - Off, **On**
- Startup Settings
 - 0 to 300 (sec.)
- Ethernet Driver Settings
 - Auto Detect
 - Off
 - Communication Mode: **Half Duplex**, Full Duplex
 - Ethernet Type: **10Base-T**, 100Base-TX
 - On
 - Mac Address
- IEEE802.1X Settings
 - Off, **On**
- Initialize Network Settings

Preferences

- Sound Volume Control
 - Fax Tone
 - Off
 - On
 - Fax Volume: **1** to 3
 - Ring Tone
 - Off
 - On
 - Ring Tone Volume: **1** to 3
 - TX Done Tone
 - Off
 - On
 - TX Done Volume: **1** to 3
 - Only When Error Occurs
 - TX Done Volume: **1** to 3
 - RX Done Tone
 - Off
 - On
 - RX Done Volume: **1** to 3
 - Only When Error Occurs
 - RX Done Volume: **1** to 3
 - Scanning Done Tone
 - Off
 - On
 - Scanning Done Volume: **1** to 3
 - Only When Error Occurs
 - Scanning Done Volume: **1** to 3
 - Entry Tone
 - Off, **On**
 - Invalid Entry Tone
 - Off, **On**
 - Restock Supplies Tone
 - Off, **On**
 - Warning Tone
 - Off, **On**
 - Job Done Tone
 - Off, **On**
 - Energy Saver Alert
 - Off, **On**
- Display Settings
 - Select Default Screen
 - Copy, Fax, Scan, USB Direct Print
 - Language
 - English^{*1}, French, Spanish, Portuguese
 - Remote UI Language
 - English^{*1}, French, Spanish, Portuguese
 - Brightness
 - 4 to **0**
 - Contrast
 - 3 to **0** to +3
 - Invert Screen Colors
 - Off, **On**
 - mm/Inch Entry Switch
 - mm, **Inch**
 - Gram/Pound Switch^{*2}
 - Gram, **Pound**
 - Message Display Time
 - 1 to **2** to 5 (sec.)
 - Scrolling Speed
 - Slow, **Normal**, Fast
 - Cursor Movement
 - Auto, Manual

* For values with "*1" mark, the default value varies depending on the country where you are using the machine.
 * For settings with "*2" mark, the setting may be unavailable depending on the country where you are using the machine.

Timer Settings

- Time & Date Settings
 - Date Display Type
 - YYYY MM/DD, **MM/DD/YYYY**, DD/MM YYYY
 - 12/24 Hour Clock
 - 12 Hour (AM/PM), 24 Hour
 - Current Time Settings^{*A}
 - Time Zone Settings
 - GMT-12:00 to GMT+12:00
 - Daylight Savings
 - Off
 - On
 - Start (M/W/D), End (M/W/D)
- Sleep Timer
 - 3 to **5** to 240 (min.)
- Auto Reset Timer
 - 0=Off, 1 to **2** to 9 (min.)
- Screen After Auto Reset
 - Default Screen, Selected Screen
- Auto Offline Time
 - 0=Off, 1 to **5** to 60 (min.)

* The settings marked with "*A" cannot be imported or exported via the Remote UI.

Common Settings

- Drawer Auto Selection
 - Copy
 - Multi-Purpose Tray: Off, **On**
 - Drawer 1: Off, **On**
 - Drawer 2*: Off, **On**
 - Printer
 - Drawer 1: Off, **On**
 - Drawer 2*: Off, **On**
 - Fax
 - Multi-Purpose Tray: Off, **On**
 - Drawer 1: Off, **On**
 - Drawer 2*: Off, **On**
 - Other
 - Multi-Purpose Tray: Off, **On**
 - Drawer 1: Off, **On**
 - Drawer 2*: Off, **On**
- Switch Paper Feed Method
 - Multi-Purpose Tray
 - Print Speed Priority, Print Side Priority
 - Drawer 1
 - Print Speed Priority, Print Side Priority
 - Drawer 2*
 - Print Speed Priority, Print Side Priority

* Settings or values with a "*" mark may not appear depending on the availability of the optional accessories.

Copy Settings

- Change Defaults

Fax Settings

- Basic Settings
 - Register Unit Telephone Number
 - Select Line Type
 - Pulse
 - Tone**
 - Off-Hook Alarm
 - Off
 - On
 - Off-Hook Alarm Volume: **1** to 3
- TX Function Settings
 - Change Defaults
 - Register Unit Name (Fax)
 - ECM TX
 - Off, **On**
 - Pause Time
 - 1 to **2** to 15 (sec.)
 - Auto Redial
 - Off
 - On
 - Redial Times: 1 to **2** to 10 (times)
 - Redial Interval: **2** to 99 (min.)
 - Redial When Err Occurs: Off, **On**
 - Sender ID
 - Off
 - On
 - Print Location: On Image, **Above Image**
 - Mark No. as: TEL/FAX: **FAX**, TEL
 - Check Dial Tone Before Sending^{*1}
 - Off, **On**
- RX Function Settings
 - ECM RX
 - Off
 - On**
 - Incoming Ring
 - Off
 - On
 - Ring Times: 1 to **2** to 99 (times)
 - Remote RX
 - Off
 - On
 - Remote RX ID: 00 to **25** to 99
 - Auto RX Switch
 - Off
 - On
 - Incoming Ring Time: 1 to **15** to 99 (seconds)
- RX Print Settings
 - 2-Sided Printing
 - Off
 - On
 - Reduce RX Size
 - Off
 - On
 - Ratio: **Auto**, 97, 95, 90, 75 (%)
 - Direction: Vertical/Horizontal, **Vertical Only**
 - RX Page Footer
 - Off, **On**
 - Continue Printing When Toner Is Low
 - Off, **On**
- Fax Setup Guide^{*A}

* The settings marked with "*A" cannot be imported or exported via the Remote UI.
 * For settings or values with "*1" mark, the setting or value may be unavailable or vary depending on the country where you are using the machine.

Scan Settings

- TX Function Settings
 - Change Defaults
 - E-Mail
 - Windows (SMB)
 - Register Unit Name (E-Mail)
- Memory Media Settings
 - Change Defaults
- Output File Image Settings
 - Color Send Gamma Value
 - Gamma 1.0, Gamma 1.4, **Gamma 1.8**, Gamma 2.2
 - PDF (Compact) Image Level
 - Image Quality in Text/Photo, Photo Mode: Data Size Priority, **Normal**, Image Quality Priority
 - Image Quality in Text Mode: Data Size Priority, **Normal**, Image Quality Priority
- Shortcut Key Settings^{*A}
 - Register
 - Scan > PC1
 - Off
 - USB Connection
 - Color Scan, B&W Scan, Custom 1, Custom 2
 - Network Connection
 - Color Scan, B&W Scan, Custom 1, Custom 2
 - Scan > PC2
 - Off
 - USB Connection
 - Color Scan, B&W Scan, Custom 1, Custom 2
 - Network Connection
 - Color Scan, B&W Scan, Custom 1, Custom 2
 - Confirm Destination

* The settings marked with "*A" cannot be imported or exported via the Remote UI.

USB Direct Print Settings

- Change Defaults
- File Sort Default Settings
 - Name (Ascending), Name (Descending), Date/Time (Ascending), Date/Time (Descending)
- File Name Format
 - Short File Name, **Long File Name**

Menu Route Map

Printer Settings	
Copies	1 to 99 (Copies)
2-Sided Printing	Off, On
Default Paper Size	LTR, LGL, STMT, EXEC, No. 10 (COM10), Monarch, DL, ISO-C5, ISO-B5, A4, A5, B5
Paper Size Override	Off, On
Print Quality	Density: -4 to 0 to 4 Toner Save: Off, On Image Refinement: Off, On
Layout	Binding Location: Long Edge, Short Edge Gutter: -1.90 to 0.00 to 1.90 (inches) Offset Short Edge (Front): -2.00 to 0.00 to 2.00 (inches) Offset Long Edge (Front): -2.00 to 0.00 to 2.00 (inches) Offset Short Edge (Back): -2.00 to 0.00 to 2.00 (inches) Offset Long Edge (Back): -2.00 to 0.00 to 2.00 (inches)
Auto Error Skip	Off, On
Timeout	5 to 15 to 300 (sec.)
Personality*	Auto, PS, PCL
PCL	Paper Save: Off, On Orientation: Portrait, Landscape Font Number: 0 to 54 Point Size: 4.00 to 012.00 to 999.75 (point) Pitch: 0.44 to 10.00 to 99.99 (dpi) Form Lines: 5 to 60 to 128 (lines) Symbol Set: PC8, PC850, PC852, PC8DN, PC8TK, PIFONT, PSMATH, PSTEXT, ROMAN8, VNINTL, VNMATH, VNUS, WIN30, WINBALT, WINL1, WINL2, WINL5, DESKTOP, ISO11, ISO15, ISO17, ISO21, ISO4, ISO6, ISO60, ISO69, ISOL1, ISOL2, ISOL5, ISOL6, LEGAL, MATH8, MCTEXT, MSPUBL, PC1004, PC775
Custom Paper	Off, On
Unit of Measure	Millimeters, Inches
X dimension	3 to 8_1/2 (inches)
Y dimension	5 to 14_0/0 (inches)
Append CR to LF	Yes, No
Enlarge A4 Print Width	Off, On
Halftones	Text: Color Tone, Resolution, Gradation, High Resolution Graphics: Color Tone, Resolution, Gradation, High Resolution Image: Color Tone, Resolution, Gradation, High Resolution
PS*	Job Timeout: 0 to 3600 (sec.) Data Protocol: Auto, ASCII, RAW/TBCP Print PS Errors: Off, On Halftones: Text: Gradation, Resolution, High Resolution Graphics: Gradation, Resolution, High Resolution Image: Gradation, Resolution, High Resolution

* The settings marked with "*" are only for MF6180dw.

Adjustment/Maintenance	
Copy Image Adjustment	
Printer Density	-4 to 0 to +4
Toner Saver Mode	Off, On
Black Text Processing for Color	Feeder: -3 to 0 to +3 Platen Glass: -3 to 0 to +3
Special Processing	Special Mode U: Off, On Special Mode V: Off, Mode 1, Mode 2 Special Mode X* (only for media printing and printing from PS/PCL printer driver): Off, Mode 1, Mode 2, Mode 3 Special Mode Z: Off, Mode 1, Mode 2, Mode 3 Special Mode B: Off, Mode 1, Mode 2, Mode 3 Special Mode C (only for printing received fax and report printing): Off, On Special Mode D: Off, On
Clean Fixing Unit	
Clean Feeder	

* The settings marked with "*" are only for MF6180dw.

System Settings	
Network Settings	-> Network Settings
System Manager Information Settings	System Manager ID and PIN: System Manager ID: Up to 7 digits, System Manager PIN: Up to 7 digits System Manager Name: Up to 32 characters
Device Information Settings	Device Name: Up to 32 characters Location: Up to 32 characters
Dept. ID Management On/Off	Dept. ID Mngt. On/Off: Off, On
Security Settings	Use SSL: Off, On IPv4 Address Filter: Send Filter: Off, On, Receive Filter: Off, On IPv6 Address Filter: Send Filter: Off, On, Receive Filter: Off, On MAC Address Filter: Send Filter: Off, On, Receive Filter: Off, On
Communication Management Settings	Fax Settings: TX Start Speed: 33600 bps, 14400 bps, 9600 bps, 7200 bps, 4800 bps, 2400 bps; RX Start Speed: 33600 bps, 14400 bps, 9600 bps, 7200 bps, 4800 bps, 2400 bps Memory Lock Settings: Off, On; Memory Lock PIN: Up to 7 digits; Report Print: Off, On; Memory Lock Time: Off, On; Memory Lock Start Time, Memory Lock End Time
Select Country/Region**A	United States (US)*, Canada (CA), Brazil (BR), Mexico (MX), Other
Forwarding Settings**A	Off, On
Store/Print When Forwarding	Print Images: Off, On, Only When Error Occurs Store Images in Memory: Do Not Store, Only When Error Occurs
Remote UI On/Off**A	Off, On
Restrict TX Function	Address Book PIN: Up to 7 digits Restrict New Destinations: Off, On Allow Fax Driver TX: Off, On Restrict History TX: Off, On Fax No. Confirmation Re-Entry: Off, On One-Touch/Coded Dial TX Confirmation: Off, On Restrict Sequential Broadcast: Off, Confirm Sequential Broadcast, Reject Sequential Broadcast
Display Job History	Off, On
USB Device On/Off	Off, On
Memory Media Storage On/Off	Off, On
USB Direct Print On/Off	Off, On
Product Extended Survey Program On/Off	Off, On
Cloud Print On/Off	Off, On
Confirm Paper Settings	Off, On
Secure Print Settings	Off, On; Secure Print Del. Time: 10 to 30 to 240 (min.)
Select PDL (Plug-n-Play)	Network: FAX, UFR II LT, UFR II LT(XPS), PCL5, PCL6, PS* USB: UFR II LT, UFR II LT(XPS), PCL5, PCL6, PS*
Update Firmware	
Initialize Key and Certificate	
Initialize Address Book	
Initialize System Settings	Network Settings System Manager Information Settings Device Information Settings Dept. ID Management On/Off Security Settings Communication Management Settings Forwarding Settings Store/Print When Forwarding Remote UI On/Off Restrict TX Function Register LDAP Server Display Job History USB Device On/Off Memory Media Storage On/Off USB Direct Print On/Off Product Extended Survey Program On/Off Cloud Print Settings Confirm Paper Settings Secure Print Settings Select PDL (Plug-n-Play) Initialize All

* The settings marked with "**A" cannot be imported or exported via the Remote UI.

* The settings marked with "*" are only for MF6180dw.

Initialize Menu	
Preferences	
Timer Settings	
Common Settings	
Copy Settings	
Fax Settings	
Scan Settings	
USB Direct Print Settings	
Printer Settings	
Initialize All	